

Scaler & media board firmware upgrade (via USB) Himalaya.

[1] Scaler ver. 1.027 for the 75BDL3003H

<https://www.dropbox.com/s/tlz0o2swl1hunrk/75BDL3003H.bin?dl=0>


1. Copy the *.bin FW file to the root directory of USB flash disk (FAT32), name the FW file same as the model name.

75BDL3000U.bin

2. Plug in the USB flash disk in the USB service port of the monitor, press remote control keys in a sequence : "home+1999+back"

This will enter the factory menu, blue window screen will popup, see picture below.


Select " Main Board Update ", then press OK




3. Monitor will display "USB update state"



4. A message “Please reboot” will appear on the monitor when fw upgrade is finished (after 2-3 mins).



5. AC repower the monitor.
6. Do a factory reset from the factory menu (press on the RC: home 1999 return)



When upgrading is failed due to interrupting the AC power it could damage the monitor or don't have any display.

If an error occurs in the update, please re-update:

1. Monitor AC OFF.
2. Copy the *.bin FW file to the root directory of USB flash disk, rename the FW file as "MERGE.bin".
3. Plug in the USB flash disk to displayer USB service port.
4. Displayer AC ON.

5. Wait about 4~5mins, when update finish,
Displayer will auto power on.

[2] Upgrade the media board firmware

The same file can be used for models:

BDL8470EU, BDL8470QT, BDL8470QU, BDL9870EU, 75BDL3000U, 75BDL3010T, 75BDL3003H

Version 1.130

https://www.dropbox.com/s/ahsfk4cohkr8pjf/upgrade_loader.pkg?dl=0

how to upgrade:

1. Switch source input to USB (Media board input).
2. insert the USB with pkg file in the monitor
3. Menu + 1 + 9 + 9 + 9 + Return by remote control unit to open the factory menu (blue page)
4. select the item "Media Board Update", then press OK.
5. software upgrade in progress should appear on the OSD (on screen display)
6. software upgrade takes about 5 mins, when finished the message "software upgrade in progress" will disappear
7. AC OFF/ON the monitor
8. do a factory reset: Menu + 1 + 9 + 9 + 9 + Return by remote control unit
select factory reset and execute